## *<del>Z</del> Tyco Electronics*

Repositioning the TPA on Unsealed **GET Market Connectors** 



Figure 1

This connector is supplied to the customer with the Terminal Position Assurance (TPA) in the pre-assembled (pre-set) position. See Figure 1, Detail "A."

During shipping and handling, the TPA may be displaced to its locked (set) position as shown in Figure 1, Detail "B."

This can prevent proper contact insertion. The connector can be returned to the proper function by retracting the TPA to the position shown in Figure 1, Detail "A." Follow the procedure below.

## **REPOSITIONING PROCEDURE**

1. Place Extraction Tool 3-1579007-6 in the gap between the housing and behind the tab on the TPA. See Figure 2.



Figure 2

2. Rotate the extraction tool toward the connector housing to "pop" the TPA into the pre-latched (disengaged) position. See Figure 3.

©2008 Tyco Electronics Corporation, Harrisburg, PA All International Rights Reserved

TOOLING ASSISTANCE CENTER 1-800-722-1111 PRODUCT INFORMATION 1-800-522-6752

TE logo and Tyco Electronics are trademarks.



**REVISION SUMMARY** 

Updated logo.

This controlled document is subject to change. For latest revision and Regional Customer Service, visit our website at www.tycoelectronics.com



Figure 3

3. Place the extraction tool tip in the gap between

the housing and TPA pulling the corners forward,

individually to disengage the side latches. See

1 of 1

\*Trademark. Other products, logos, and company names used are the property of their respective owners.