



CONNECTOR TYPE	CABLE TYPE	TOOLS REQUIRED:
OSM STRAIGHT CABLE PLUG, RETRACTABLE COUPLING NUT DIRECT SOLDER ATTACHMENT	.085 SEMI-RIGID COAXIAL CABLE	FIXTURE BASE: 2098-3206-54 (T-4567) CLAMP INSERT: 2098-5208-54 (T-4700-2) CENTER CONTACT HOLDER: 2098-5221-10 (T-4578) SOLDER GAGE: 2098-5518-02 (T-4582-5) LOCATOR TOOL: 2098-0307-02 DIELECTRIC INSERT TOOL: 2098-0295-02

CONNECTOR




ASSEMBLY OPERATIONS


- 1.0 PREPARATION OF CABLE**
- 1.1 INSERT SQUARED CABLE END INTO FIXTURE BASE HOLE PATTERN #2.
 - 1.2 PLACE SAW IN SAW SLOT AND CUT THROUGH OUTER CONDUCTOR AND INTO DIELECTRIC WHILE ROTATING CABLE.
 - 1.3 REMOVE CABLE FROM FIXTURE AND FINISH CUTTING DIELECTRIC WITH CUTTING BLADE.
 - 1.4 BARE INNER CONDUCTOR BY PRYING CUT OUTER CONDUCTOR AND DIELECTRIC FROM CABLE.




- 2.0 SOLDERING OF CENTER CONTACT TO CABLE INNER CONDUCTOR**
- 2.1 TIN INNER CONDUCTOR OF CABLE.
 - 2.2 PLACE SOLDER GAGE ON INNER CONDUCTOR, FLUSH WITH END OF OUTER CONDUCTOR.
 - 2.3 PLACE CENTER CONTACT IN HOLDER, HEAT CENTER CONTACT AND PUSH IT OVER INNER CONDUCTOR OF CABLE TO REST FIRMLY AGAINST SOLDER GAGE.
 - 2.4 REMOVE SOLDER GAGE AND EXCESS SOLDER.



- 3.0 SOLDERING OF CABLE SUB-ASSEMBLY TO HOUSING**
- 3.1 PLACE COUPLING NUT AND HOUSING ON END OF CABLE.
 - 3.2 PLACE LOOSE ASSEMBLY IN FIXTURE BASE AS SHOWN.
 - 3.2.1 NEST CENTER CONTACT IN LOCATOR TOOL.
 - 3.2.2 TIGHTEN CLAMP SCREW TO SECURE CABLE.
 - 3.2.3 TIGHTEN LOCATOR TOOL TO SEAT CABLE FIRMLY.
 - 3.3 SLIDE HOUSING OVER LOCATOR TOOL.
 - 3.4 MAINTAIN POSITION OF HOUSING FIRMLY AGAINST LOCATOR TOOL AND SOLDER.
- NOTE: FIXTURE SHOULD BE CLAMPED VERTICALLY IN VISE TO KEEP HOUSING SEATED AGAINST LOCATOR TOOL.



- 4.0 PRESSING OF DIELECTRIC BUSHING INTO HOUSING SUB-ASSEMBLY**
- 4.1 SLIDE COUPLING NUT FORWARDING SUB-ASSEMBLY.
 - 4.2 INSERT DIELECTRIC INTO HOUSING.
 - 4.3 PLACE INSERT TOOL PLUNGERS INTO POSITION AND PRESS UNTIL FLANGES FORM ON TOOL HOUSING.



- 5.0 SECURE COUPLING NUT TO HOUSING**
- 5.1 SLIDE NUT BACK AND PLACE GASKET ON HOUSING.
 - 5.2 SLIDE COUPLING NUT ONTO HOUSING.
 - 5.3 SNAP RETAINING RING IN HOUSING GROOVE JUST BEHIND COUPLING NUT.
 - 5.4 COUPLING NUT SHOULD ROTATE FREELY.
 - 5.5 ASSEMBLY IS NOW COMPLETE.



- 6.0 INSPECTION OF COMPLETED CONNECTOR ASSEMBLY**
- 6.1 ADHERENCE TO STEPS GIVEN WILL YIELD TOLERANCES SHOWN.

