



POSITION	CONNECTOR		COVER			
	PLUG	RECEPTACLE	LOOSE-PIECE	BULK PACK KIT NO.	INDIVIDUAL KIT NO.	
9	745203 & 745492	745201 & 745491	745529-1	745530-5	745530-1	
15	745207 & 745494	745205 & 745493	-2	-6	-2	
25	745211 & 745496	745209 & 745495	-3	-7	-3	
37	745215 & 745498	745213 & 745497	-4	-8	-4	

Fig. 1

### 1. INTRODUCTION

This instruction sheet (IS) covers the use of the AMPLIMITE HDE-20 Low Profile Slide-On Covers listed in Figure 1. Read these instructions carefully before using the covers.

### 2. DESCRIPTION (Figure 1)

Each individual cover kit consists of two symmetrical covers which snap together over the AMPLIMITE HDE-20 Connector (either plastic or metal shell).

Each cover features a locking latch and track which holds the latch, allowing the two covers to lock together.

The cover kit can be used with plug and receptacle connectors in 9, 15, 25, and 37 circuit positions.

### 3. INSTALLATION PROCEDURES

Refer to the chart in Figure 1 and select the appropriate cover kit and connector and proceed as follows:

- Slide one cover of the kit over exposed contacts of connector, making sure track of cover fits into channel on connector.
- Slide the other cover onto connector, allowing the locking latches to snap into the tracks.

### 4. EXTRACTION PROCEDURES

Refer to Figure 1 and proceed as follows:

- Insert a thin or pointed instrument into the track and depress one locking latch. Repeat the procedure on the other side.
- Pull the covers apart.

Copyright 1981 by AMP Incorporated, Harrisburg, Pa. All International Rights Reserved. AMP Incorporated products covered by U.S. and Foreign patents and/or patents pending.