



## Introducing Cable grip, BB type

- These cable grips are used to connect a conductor:
  - On a metallic armature
  - On a galvanized or aluminium framework with a bimetallic washer

### DESCRIPTION

- These cable grips are made of a body which receives the bare cable
- They are made of copper alloy
- To fix these parts, versatile supports with specific studs are available: metal or wood according to the material to which this product is fixed.

### KEY FEATURES and BENEFITS

Accept round conductors up to 240mm <sup>2</sup>	One technology for a large size of cable
Made out of brass	Corrosion free
Various studs are available	Can be used on various structures

### PRODUCT PHOTOS & DIMENSIONS



While TE Connectivity (TE) has made every reasonable effort to ensure the accuracy of the information in this catalog, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications. AMP, Raychem, SIMEL, TE Connectivity and TE Connectivity (logo) are trademarks.

Tyco Electronics Simel S.A.S. – TE Energy

1, Rue Paul Martin 21220 Gevrey-Chambertin Tel: 00 (33) 3 80 58 32 00 Fax: 00 (33) 3 80 34 10 15

[Energy.te.com](http://Energy.te.com)

SIM068Rev3 Energy PDF Aug 2012

## PRODUCT DIMENSIONS

Designation	TCPN	Capacity			Dimensions				Weight (Kg)	Std pack
		$\phi$ mm	mm <sup>2</sup>	M	A	$\phi$ D	P	L		
BB 6-6	0-0709305-2	3 to 6	6 to 16	6x100	6.3	16.8	17	19	0.0251	50
BB 6-7	0-0709305-3	3 to 6	6 to 16	7x150	6.3	16.8	17	19	-	50
BB 6-8	0-0709305-4	3 to 6	6 to 16	8x125	6.3	16.8	17	19	0.0248	50
BB 8-6	0-0709305-6	4 to 8	10 to 35	6x100	8.3	17.8	18	22	0.0321	50
BB 8-7x150	0-0709305-7	4 to 8	10 to 35	7x150	8.3	17.8	18	22	0.0313	50
BB 8-8	0-0709305-8	4 to 8	10 to 35	8x125	8.3	17.8	18	22	0.0307	50
BB 8-10	0-0709305-9	4 to 8	10 to 35	10x150	8.3	17.8	18	22	-	50
BB 8-12	1-0709305-0	4 to 8	10 to 35	12x175	8.3	17.8	18	22	-	50
BB 10-6	1-0709305-3	7 to 10	25 to 50	6x100	10.3	20.8	21	26	0.0488	25
BB 10-7x150	1-0709305-4	7 to 10	25 to 50	7x150	10.3	20.8	21	26	0.0480	25
BB 10-8	1-0709305-5	7 to 10	25 to 50	8x125	10.3	20.8	21	26	-	25
BB 10-10	1-0709305-6	7 to 10	25 to 50	10x150	10.3	20.8	21	26	-	25
BB 12-6	1-0709305-8	8 to 12	35 to 95	6x100	12.3	23.8	24	30	-	25
BB 12-7x150	1-0709305-9	8 to 12	35 to 95	7x150	12.3	23.8	24	30	0.0684	25
BB 12-8	2-0709305-0	8 to 12	35 to 95	8x125	12.3	23.8	24	30	0.0676	25
BB 12-10	2-0709305-1	8 to 12	35 to 95	10x150	12.3	23.8	24	30	-	25
BB 12-12	2-0709305-2	8 to 12	35 to 95	12x175	12.3	23.8	24	30	0.0658	25
BB 14-6	2-0709305-4	8 to 14	35 to 120	6x100	14.3	26	26	34	0.0884	25
BB 14-7x150	2-0709305-5	8 to 14	35 to 120	7x150	14.3	26	26	34	0.0882	25
BB 14-8	2-0709305-6	8 to 14	35 to 120	8x125	14.3	26	26	34	-	25
BB 14-10	2-0709305-7	8 to 14	35 to 120	10x150	14.3	26	26	34	-	25
BB 14-12	2-0709305-8	8 to 14	35 to 120	12x175	14.3	26	26	34	-	25



While TE Connectivity (TE) has made every reasonable effort to ensure the accuracy of the information in this catalog, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications. AMP, Raychem, SIMEL, TE Connectivity and TE Connectivity (logo) are trademarks.


Tyco Electronics Simel S.A.S. – TE Energy

1, Rue Paul Martin 21220 Gevrey-Chambertin Tel: 00 (33) 3 80 58 32 00 Fax: 00 (33) 3 80 34 10 15

[Energy.te.com](http://Energy.te.com)

SIM068Rev3 Energy PDF Aug 2012


## Cable grip for cable on framework



Designation	TCPN	Capacity (mm <sup>2</sup> )	Dimensions (mm)					Weight (g)	Standard packaging
			A	∅B or B	H	∅ ext	∅ int		
SF 12-7 +BM	716090-1	75	12.5	24	30	30	8.5	-	25
SF 14+7 BM	710116-1	116	14.5	26	34	30	8.5	-	25
SF 16+7 BM	716091-1	147	16.5	30	40	30	8.5	-	25
SF 20-7 +BM	716092-1	181*	-	46	19.5	30	8.5	-	10

\* could be used up to 240mm<sup>2</sup>

## Aluminium copper washer



Designation	TCPN	Dimensions DxdxE (mm)	Weight (g)	Standard Packaging
Washer Alu-Cu	709581-1	30x6.56x5	--	100
Washer Alu-Cu	709580-1	30x8.5x2	--	100
Washer Alu-Cu	711621-1	30x10.5x2	--	100
Washer Alu-Cu	707841-1	30x13x2	--	100



While TE Connectivity (TE) has made every reasonable effort to ensure the accuracy of the information in this catalog, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications. AMP, Raychem, SIMEL, TE Connectivity and TE Connectivity (logo) are trademarks.

Tyco Electronics Simel S.A.S. – TE Energy

1, Rue Paul Martin 21220 Gevrey-Chambertin Tel: 00 (33) 3 80 58 32 00 Fax: 00 (33) 3 80 34 10 15

[Energy.te.com](http://Energy.te.com)

SIM068Rev3 Energy PDF Aug 2012