

SIMAFLEX SUBSTATION CONNECTOR SYSTEM FOR ALUMINUM FLEXIBLE CABLE CONNECTIONS UP TO 500 kV

KEY FEATURES

- Designed to withstand the high mechanical stress of Extra High Voltage (EHV) substations
- Customizable to application requirements offering 2-3 keeper solutions from one product range
- High electrical performance with in-house machining combined with waxed bolts
- Short lead time thanks to casted components produced inhouse
- Adjustable connectors

TE Connectivity's (TE) SIMAFLEX is a product line of extra high voltage substation clamps and connectors, designed for stranded bare conductors in AC & DC applications up to 550 kV for both Metric and Imperial sizes.

The range includes mechanical support, derivations, connections to terminal equipment (stud & pads), transition connection to rigid aluminum busbars, as well as accessories such as earthing stirrups and spacers.

The Metric range covers connectors for aluminum stranded conductors from 15 mm always to 59 mm O/D and transition connections to aluminum tubular conductors from 80 mm O/D up to 250 MM O/D.

The Imperial range covers connectors for aluminum stranded conductors from 266.8 MCM (0.609") and up to 3500 MCM (2.159") and transition connections to aluminum tubular conductors from 2.5" to 6" for both SPS and EHPS dimensions.

Connections for Single, Twin, Triplex and Quad conductors bundle configurations are available from 100 MM (4") to 450 MM (18").

Customers can count on consistent, high quality products, driven by TE's proven innovation and backed by our extraordinary customer support.







TECHNICAL DATA

Voltage	63 kV to 550 kV (depending on the conductor's bundle configuration)				
Current	100 A and up to 6000 A				
Short-time current	40 kA / 3 sec and up to 80 kA / 1sec				
Connector size/ conductor size	Small 15 to 32,5 mmMedium 28,6 to 42,5 mmLarge 42,6 to 59 mm				
Conductor's bundle spacing	100 mm through 200 mm, 400 mm to 450 mm				
Terminal fixing (stud)	Solid studs in aluminum or copper from 30 mm to 60 mm O/D				
Terminal fixing (pad)	From 80x80 mm to 100x200 mm				
Post insulator's interfaces	76 MM PCD to 275 MM PCD				
Material	High-grade aluminum alloy				
Fasteners	M10/M12 Bolts in stainless steel with pre-waxed nuts to ensure pressure contact efficiency and contact reliability. Avoids bolts seizing during tightening operation.				
Standards	EN (IEC), ANSI/NEMA & DIN Compliant				



SMALL - 2 keepers



MEDIUM - 2 OR 3 keepers



LARGE - 2 OR 3 keepers

220

220

250

250

200

200

TERMINAL STUDS

Busbar Size

O/D

Available from 30mm, 40mm, 50mm to 60 mm diameter in both aluminum and copper material

90

90

TERMINAL PADS CONNECTIONS

Metric

(mm)

Available from 80x80, 100x100, 125x125, to 100x20 mm according to IEC, NF, NEMA and DIN standards

100

100

120

120

125

125

140

140

150

150

160

160

STANDARD	N° HOLES	L	I	Α	В	С	D
IEC		80	80	40	40	20	14.5
NEMA		80	80	44.4	44.4	15.3	14.3
NF	4	80	80	45	45	16.5	16
IEC	4	100	100	40	40	30	14.5
NEMA		100	100	44.4	44.4	27.8	14.3
DIN		100	100	50	50	25	14.5
IEC	6	100	125	40	40	30	14.5
NEMA		10	125	44.4	44.4	27.8	14.3
DIN	8	100	200	50	50	25	14.5
IEC	9	125	125	40	40	22.5	14.5
NF		125	125	45	45	16.5	16

ALUMINUM BUS SIZES (FOR TRANSITION CONNECTORS)

80

80





POST INSULATOR FIXING

Available from 76 PCD through 127 PCD, 178 PCD, 225 PCD, 254 PCD and up to 275 PCD

PCD (mm)	N° HOLES	D
3 Inch	4	0.56″
5 Inch		0.7"
7 Inch	8	0.86″
8.86 Inch (225 mm)		0.7"
10 Inch		0.7"
10.8 Inch (275 mm)		0.7"











TECHNICAL DATA				
Voltage	63 kV to 550 kV (depending on the conductor's bundle configuration)			
Current	100 A and up to 6000	100 A and up to 6000 A		
Short-time current	40 kA / 3 sec and up t	o 55 kA / 1sec		
Connector size/ conductor size	Small Medium Large 266.8 to 1200 MCM 795 to 2000 MCM 2250 to 3500 MCM			
Conductor's bundle spacing	4", 6" 8", 12", 16" and up to 18" nominal			
Terminal fixing (stud)	Threaded studs in aluminum or copper from 1-1/2", 2", 2-1/2" and 3"			
Terminal fixing (pad)	From 3" x 3", 4" x 4" 4" x 5", 4" x 6"			
Post insulator's interfaces	3" PCD and up to 10 Inch PCD			
Material	High-grade aluminum alloy			
Fasteners	Stainless steel hardware with pre-waxed nuts to ensure pressure contact efficiency and contact reliability. Avoids bolts seizing during tightening operation.			
Standards	ANSI/NEMA & DIN Compliant			



SMALL - 2 keepers



MEDIUM - 2 OR 3 keepers



LARGE - 2 OR 3 keepers

6″

5.625

5″

5.563

ALUMINUM BUS SIZES (FOR TRANSITION CONNECTORS) BUSBAR SIZE Imperial O/D (Inch)

TERMINAL STUDS

Available from 1-1/2", 2", 2-1/2", 3" Dia in both aluminum or copper material

TERMINAL PADS CONNECTIONS

Available from 3" x 3 " through 4" x 4", 4" x 5", 4" x 6" NEMA standards and up to 4" x 8" according to DIN standards

2.5 "

2.875

3″

3.5

STANDARD	N° HOLES	L	I	Α	в	с	D
4	3″	3″	1.75″	1.75″	0.63″	0.56″	
	4	4″	4″	1.75″	1.75″	1.13″	0.56″
	4″	5″	1.75″	1.75″	1.13″	0.56″	
	6	4″	6″	1.75″	1.75″	1.13″	0.56″
DIN	8	4″	8″	1.97″	1.97″	1″	0.57″



3.5″

4

4″

4.5



POST INSULATOR FIXING

Available from 3"PCD through 5"PCD, 7" PCD, 8.86" (225) PCD, 10" PCD and up to 10.8" (275) PCD

PCD (mm)	N° HOLES	D
3 Inch	4	0.56″
5 Inch		0.7"
7 Inch	8	0.86″
8.86 Inch (225 mm)		0.7"
10 Inch		0.7"
10.8" (275 mm)		0.7"





TE Connectivity Ltd. is a \$13 billion global industrial technology leader creating a safer, sustainable, productive, and connected future. Our broad range of connectivity and sensor solutions, proven in the harshest environments, enable advancements in transportation, industrial applications, medical technology, energy, data communications, and the home. With nearly 80,000 employees, including more than 8,000 engineers, working alongside customers in approximately 150 countries, TE ensures that EVERY CONNECTION COUNTS. Learn more at www.TE.com and on LinkedIn, Facebook, WeChat and Twitter.

CONNECT WITH US: TE.com/energy-contact

TE CUSTOMER CARE CENTERS (Countries/Regions)

AMERICAS

USA/Canada	+1 800-327-6996	Australia
Brazil	+55 11-2103-6023	China
Mexico	+52 55-1106-0800	Hong Ko
South America	+57 1-319-8962	Indones

EUROPE-MIDDLE EAST-AFRICA

Benelux	+32 16-508-695
Czech Republic	+42 (0) 272-011-105
France	+33 (0) 38-058-3210
Germany/Switzerland	+49 (0) 89-608-9903
Italy	+39 335-834-3453
Middle East/Africa	+971 4-211-7020
Poland/Baltics	+48 224-576-753
Russia	+7 495-790-790-2-200
Spain/Portugal	+34 912-681-885
Sweden/Norway	+46 850-725-000
UK	+44 08708-707-500

ASIA-PACIFIC

Australia
China
Hong Kong/Taiwan
Indonesia
Japan
Korea
Malaysia
New Zealand
Philippines
Singapore
Thailand
Vietnam

+61 29-554-2695 +86 (0) 400-820-6015 +852 2738-8195 +62 21-2929-3816 +44 844-8446 +82 2-3415-4625 +60 3-7806-7731 +64 9-634-4580 +63 2-988-9445 +65 65-90-5151 +66 2-834-6294 +84 28-3911-5025 (ext. 105)

TE.com/energy

© 2020 TE Connectivity. All Rights Reserved. EPP-00038-02/20

TE Connectivity, TE connectivity (logo), EVERY CONNECTION COUNTS, AMP, AMPACT, Axicom, Bowthorpe EMP, Crompton Instruments, Raychem, SIMEL, UTILUX are trademarks. Other logos, product and Company names mentioned herein may be trademarks of their respective owners. While TE has made every reasonable effort to ensure the accuracy of the information in this brochure, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this brochure are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications.

