


Universal double branch joint connectors

UBRD connectors are designed for jointing low voltage aluminium and copper conductors where two cables are to be jointed to the main.

The connector body and shear-head bolts are aluminium alloy. UBRD95 range requires a 13mm socket or spanner to complete the installation. UBRD185 & UBRD 300 ranges requires a 19mm socket or spanner.

For jointing sectorial conductors with 'V' facing up or down



DATA SHEET Date: 01/12/2012 Number: EPP-1734 Revision: B


Features

- Can be used as a transition connector between cables with different conductor constructions, types, materials and sizes (e.g. solid sectoral to circular stranded)
- The standard product is supplied with shear head bolts
- Low torque, direct acting bolts

Standards

• Meets requirements of BS4579 and IEC 61238-1 (2003)





| Reference | PN | TCPN | Dimensions (mm) | | | Conductor size | Socket/spanner A/F (mm) |
|-----------|---------------|------------|--------------------|----|----|-------------------|----------------------------|
| | | | L | н | W | (mm²) | |
| UBRD95 | BAH-023000040 | 732988-000 | 80 | 38 | 50 | 35 - 95 | 13 |
| UBRD185 | BAH-023000043 | 185992-000 | 108 | 47 | 67 | 35 - 185 | 19 |
| UBRD300 | BAH-023000048 | 733882-000 | 108 | 54 | 78 | 70 - 300 | 19 |

While TE Connectivity (TE) has made every reasonable effort to ensure the accuracy of the information in this catalog, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications. TE Connectivity and TE connectivity (logo) are trademarks.

TE Energy – innovative and economical solutions for the electrical power industry: cable accessories, connectors & fittings, insulators & insulation, surge arresters, switching equipment, street lighting, power measurement and control.

Tyco Electronics UK Ltd a TE Connectivity company Freebournes Road Witham, Essex CM8 3AH

Phone: +44 (0)870 870 7500 Fax: +44 (0)870 240 5289 Email: ukutilities@tycoelectronics.com

energy.te.com

