

FUSE BOXES EKM-1270, EKM-1272, EKM-1275

FUSE BOX FOR APPLICATION IN LIGHTING POLES

KEY FEATURES

- Suitable for application in lighting poles with diameter ≥ 90 mm
- Mantle terminals allow simple and secure connection up to 16 mm²
- Touch proof at maintenance even with removed cover
- EKM-1270 and EKM-1275 have thermally rigid and tracking resistant ceramic bases

TE Connectivity's (TE) EKM-1270, EKM-1272 and EKM-1275 provide a solution for connection and protection of luminaires in lighting poles and outdoor, that has proven its reliability over decades.

With its mantle terminals EKM-127x can be installed fast and reliably in all street lighting grids.

Customers can count on consistent, high quality products, driven by TE's proven innovation and backed by our extraordinary customer support.









TECHNICAL DATA				
Detail	Data			
Application range	inside of lighting poles			
Pole inner diameter	≥ 90 mm			
Min. dimension of hand hole W x H	80 x 260 mm			
Degree of protection	IP 43			
Protection class	II			
Cable cross section feeder cable	1/2 x 4/5 x 6 - 16 mm ² (cable dia. 2 x 22 mm)			
Cable cross section luminaire cable	1 x 3 x 1,5 mm ² - 1 x 5 x 2,5 mm ² (cable dia. 8-14 mm)			
Dimensions H x W x D	250 x 76 x 85 mm			
Feeder cable terminals	4- / 5- pole with mantle terminals			
Fuse system	2 X D II (E27)			
Pinning	universal			
Protection against contact to life parts	acc. BGV A3			
Material	thermoplastic material			
Cover details	cover with latch			
Luminaire cable sealing	1 x Pg 16 compression gland			

PRODUCT SELECTION INFORMATION							
Description		for 1 cable (mm²)	for 2 cables (mm²)	for 3 cables (mm²)	Part Number		
EKM-1270-2D2-4X16	2 fuseholder-ceramic DII (E27), 4 mantle terminals	4 x 6 - 16	4 x 6 - 16		621630-000		
EKM-1272-2D2-5X16-B	2 fuseholder DII (E27), 5 mantle terminals	5 x 6 - 16	5 x 6 - 16		133336-000		
EKM-1275-2D2-5X16	2 fuseholder-ceramic DII (E27), 5 mantle terminals	5 x 6 - 16	5 x 6 - 16		251978-000		

te.com/energy

©2014 TE Connectivity Ltd. family of companies. All Rights Reserved. EPP-2374-10/14

TE Connectivity and TE connectivity (logo) are trademarks. Other logos, product and/or company names might be trademarks of their respective owners. While TE has made every reasonable effort to ensure the accuracy of the information in this brochure, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this catalog are for reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications.

FOR MORE INFORMATION: TE Technical Support Centers

USA: + 1 800 327 6996 + 33 380 583 200 + 44 0870 870 7500 France: UK: + 49 896 089 903 Germany: Spain: + 34 916 630 400 Benelux: + 32 16 351 731 Canada: +1 (905) 475-6222 + 52 (0) 55-1106-0800 + 54 (0) 11-4733-2200 Mexico: Latin/S. America: + 86 (0) 400-820-6015 China:

