

MECHANICAL CONNECTORS AND REPAIR SLEEVES BSM

FOR LOW AND MEDIUM VOLTAGE APPLICATION UP TO 42 kV

KEY FEATURES

- Wide application range
- Compact design
- Can be used with almost every type of conductor and material
- Torque-controlled shear head bolts guarantee an excellent electrical contact
- Easy installation with standard socket spanner
- Pre-engineered design for perfect fit in medium voltage cable accessories up to 42 kV
- Tested according to IEC 61238-1 class A

TE Connectivity's (TE) mechanical connectors and repair sleeves BSM are designed for use in low and medium voltage applications. Three sizes of BSM connectors cover conductor sizes ranging from 25 mm² to 400 mm². Our connectors consist of a tin-plated body, shear bolt heads and inserts for small conductor sizes.

Made of special aluminium alloy, these contact bolts are double shear bolt heads with hexagon heads. The bolts are treated with a highly lubricating agent. Contact bolts are irremovable once their heads have been sheared off. The lug body is made of a high-tensile, tin-plated aluminium alloy. The internal surface of the conductor holes are grooved.

The connectors are chamfered at the edges and available with or without oil barrier (as blocked and unblocked types) depending on the application requirements. The bolted fitting featured herein was developed specifically for use in medium voltage cable accessories up to 42 kV. They may also be used in the 1 kV range.

Before using mechanical connectors in cable accessories, confirm that they are suitable for the given application and if necessary consult our experts.

Customers can count on consistent, high quality products, driven by TE's proven innovation and backed by our extraordinary customer support.













BSMB 25/95-95/240	PRODUCT SELECTION INFORMATION													
Name	Description			Disalisad	Dimensions (mm)						Contact		Head Size	
BSMB-10/35	Description			вюскеа	L1	L2	D1	D2	D3	D4	Bolts Quantity		AF (mm)	
SSM-25/95														
BSM-25/95-U 25-95	BSMB-10/35	10 - 35		ves	45	20	19	8,5	-	-	2		10	
BSMB-35/150 35 - 150 yes 80 35 28 15.8 -	BSM-25/95			yes	65	30	24	12,8	-	-	2		13	
BSMU-35/150	BSM-25/95-U			no	65				-	-				
BSM-95/240	BSMB-35/150	35 - 150		yes		35		15,8	-	-				
BSMB-95/240-JU	BSMU-35/150			no					-	-				
BSMB-95/240-34				yes		60			-	-	·			
BSMB-120/300 120 - 300 yes 140 65 37 24 -				no					-	-				
BSMU-120/300				yes			-		-	-				
BSMB-150/400				yes										
BSMU-150/400				no					-	-	· · · · · · · · · · · · · · · · · · ·			
BSMB-500mk2				yes						-				
BSMB-630mk2				no					-	-				
BSMB-800mk2				yes					-	-				
Reduction Connectors				yes					-	-				
Reduction Connectors Side 1 Side 2 BSMB 25/95-95/240 25 - 95 95 - 240 yes 125 60 24 12,8 33 20 1 2 13 19 BSMB 95/240-185/400 95 - 240 185 - 400 yes 170 80 33 20 42 25,5 2 3 19 22 BSMB 185/400-500 185 - 400 500 yes 190 90 42 25,5 2 3 19 22 BSMB 185/400-630 185 - 400 500 yes 190 90 42 25,5 46 30 3 3 22 27 BSMB 500-630mk2 500 630 yes 160 70 46 30 50 33 3 3 22 27 BSMB 500-800 500 800 yes 180 85 46 30 56 36 3 4 13 13 BSMB 630-1000 <t< th=""><th></th><th colspan="2"></th><th>yes</th><th></th><th></th><th></th><th></th><th>-</th><th>-</th><th colspan="2"></th><th colspan="2"></th></t<>				yes					-	-				
BSMB 25/95-95/240	BSMB-1000	1000		yes	180	85	60	40	-		3	3	13	
BSMB 95/240-185/400 95 - 240 185 - 400 yes 170 80 33 20 42 25,5 2 3 19 22											Side 1	Side 2		Side 2
BSMB 185/400-500 185 - 400 500 yes 190 90 42 25,5 46 30 3 3 22 27	BSMB 25/95-95/240	25 - 95		yes	125	60			33		1	2	13	
BSMB 185/400-630 185 - 400 630 yes 200 95 42 25,5 50 33 3 22 27 BSMB 500-630mk2 500 630 yes 160 70 46 30 50 33 3 3 13 13 BSMB 500-800 500 800 yes 180 85 46 30 56 36 3 4 13 13 BSMB 630-800 630 800 yes 180 85 50 33 56 36 3 4 13 13 BSMB 630-1000 630 1000 yes 180 85 50 33 60 40 3 4 13 13 BSMB 800-1000 800 1000 yes 180 85 56 36 60 40 3 4 13 13 BSMV-120/300 120 - 300 yes 160 65 37 24 <t< th=""><th></th><th></th><th></th><th>yes</th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th><th></th></t<>				yes										
BSMB 500-630mk2 500 630 yes 160 70 46 30 50 33 3 3 13 13 13 13 13				yes										
BSMB 500-800				yes	200									
BSMB 630-800 630 800 yes 180 85 50 33 56 36 3 4 13 13 13 BSMB 630-1000 630 1000 yes 180 85 50 33 60 40 3 4 13 13 13 BSMB 800-1000 800 1000 yes 180 85 56 36 60 40 3 4 13 13 13 13 13 13 13 13 13 13 13 13 13				yes										
BSMB 630-1000				yes								-		
Split Connectors				yes										
Split Connectors Contact Central Head Size AF AF Contact Central AF Contact Central Central AF Contact Central Cen														
Split Connectors Contact Central AF Contact Central AF Contact Central Central BSMV-120/300 120 - 300 yes 160 65 37 24 4 -	BSMB 800-1000	800	1000	yes	180	85	56	36	60	40	3	4		
Contact Central BSMV-120/300 120 - 300 yes 160 65 37 24 4 - 4 1 22 21 21 22 21 23 24 30 24 25,5 6 - 6 1 22 19 20 20 20 20 20 20 20 2														
BSMV-120/300 120 - 300 yes 160 65 37 24 4 - 4 1 22 21 BSMV-185/400 185 - 400 yes 190 80 42 25,5 6 - 6 1 22 19 Mechanical Repair Sleeves BSM-25/95-U-L440 25 - 95 no 440 30 24 12,8 - - 2 13 BSM-95/240-U-L440 95 - 240 no 440 60 33 20 - - 4 19 BSMU-95/240-34-L440 95 - 240 no 440 60 34 22 - - 4 19	Split Connectors										Contact	Central		AF Central
BSMV-185/400 185 - 400 yes 190 80 42 25,5 6 - 6 1 22 19 Mechanical Repair Sleeves BSM-25/95-U-L440 25 - 95 no 440 30 24 12,8 - - 2 13 BSM-95/240-U-L440 95 - 240 no 440 60 33 20 - 4 19 BSMU-95/240-34-L440 95 - 240 no 440 60 34 22 - 4 19	BSMV-120/300	120 -	120 - 300		160	65	37	24	4	-	4	1		
BSM-25/95-U-L440			185 - 400							-		1		
BSM-95/240-U-L440 95 - 240 no 440 60 33 20 4 19 BSMU-95/240-34-L440 95 - 240 no 440 60 34 22 4 19														
BSMU-95/240-34-L440 95 - 240 no 440 60 34 22 4 19	BSM-25/95-U-L440	25 -	- 95	no	440	30	24	12,8	-	-	2		13	
BSMU-95/240-34-L440 95 - 240 no 440 60 34 22 4 19	BSM-95/240-U-L440	95 -	240	no	440	60	33	20	-	-	<u> </u>		19	
	BSMU-95/240-34-L440	95 -	240	no		60	34	22	-	-				
BSMU-120/300-L440 120 - 300 no 440 65 37 24 - - 4 22	BSMU-120/300-L440	120 -	120 - 300		440	65	37	24	-	-	4		22	
BSM-185/400-U-L440 185 - 400 no 440 80 42 25,5 6 22	BSM-185/400-U-L440	185 -			440	80	42	25,5	_					
BSMU-500-L440 500 no 440 90 46 30 6 27	BSMU-500-L440			no	440	90	46	30	-	-			27	











te.com/energy

© 2018 TE Connectivity. All Rights Reserved. EPP-2287-DDS-10/18-EN

TE Connectivity and the TE connectivity (logo) are trademarks of the TE Connectivity Ltd. family of companies. Other logos, product and Company names mentioned herein may be trademarks of their respective owners. While TE has made every reasonable leaffort to ensure the accuracy of the information in this brochure, TE does not guarantee that it is error-free, nor does TE make any other representation, warranty or guarantee that the information is accurate, correct, reliable or current. TE reserves the right to make any adjustments to the information contained herein at any time without notice. TE expressly disclaims all implied warranties regarding the information contained herein, including, but not limited to, any implied warranties of merchantability or fitness for a particular purpose. The dimensions in this brochure are reference purposes only and are subject to change without notice. Specifications are subject to change without notice. Consult TE for the latest dimensions and design specifications.

FOR MORE INFORMATION: TE Technical Support Centers

USA: + 1 800 327 6996 Canada: +1(905)475-6222 + 52 (0) 55-1106-0800 Mexico: Latin/S. America: + 54 (0) 11-4733-2200 France: + 33 380 583 200 UK: + 44 0870 870 7500 + 49 89 6089 903 Germany: + 34 916 630 400 Spain: + 39 333 250 0915 Italy: Benelux: + 32 16 508 695 Russia: + 7 495-790 790 2-200 China: + 86 (0) 400-820-6015

